

CS4334/5/6/7/8/9

8-Pin, 24-Bit, 96 kHz Stereo D/A Converter

The following information is based on the technical datasheet:

CS4334/5/6/7/8/9 DS248PP1 APR '98

Please contact Cirrus Logic : Crystal Semiconductor Products Division for further information.

CRYSTAL SEMICONDUCTOR PRODUCTS DIVISION PRODUCT INFORMATION

Copyright © Cirrus Logic, Inc. 1998
(All Rights Reserved)

PI248PP1 APR '98



CS4334/5/6/7/8/9 Features

8-Pin, 24-Bit, 96 kHz Stereo D/A Converter

Features

- Complete Stereo DAC System: Interpolation, D/A, Output Analog Filtering
- 24-Bit Conversion
- 96 dB Dynamic Range
- 0.003% THD
- Low Clock Jitter Sensitivity
- Single +5 V Power Supply
- Filtered Line Level Outputs
- On-Chip Digital De-emphasis
- Soft Ramp to Quiescent Output Voltage
- Functionally Compatible with CS4330/31/33

Description


The CS4334 family members are complete, stereo digital-to-analog output systems including interpolation, 1-bit D/A conversion and output analog filtering in an 8-pin package. These devices differ in the serial interface format used for audio data input.

The CS4334 family is based on delta-sigma modulation, where the modulator output controls the reference voltage input to an ultra-linear analog low-pass filter. This architecture allows for infinite adjustment of sample rate between 2 kHz and 100 kHz simply by changing the master clock frequency.

The CS4334 family contains on-chip digital de-emphasis, operates from a single +5 V power supply, and requires minimal support circuitry. These features are ideal for portable CD players and other portable playback systems.



CS4334/5/6/7/8/9 Overview



Overview

The CS4334 family of devices offers a complete stereo digital-to-analog system including digital interpolation, fourth-order delta-sigma digital-to-analog conversion, digital de-emphasis and analog filtering. This architecture provides a high tolerance to clock jitter.

The primary purpose of using delta-sigma modulation techniques is to avoid the limitations of laser trimmed resistive digital-to-analog converter architectures by using an inherently linear 1-bit digital-to-analog converter. The advantages of a 1-bit digital-to-analog converter include: ideal differential linearity, no distortion mechanisms due to resistor matching errors and no linearity drift over time and temperature due to variations in resistor values.

The CS4334 family of devices supports two modes of operation. The devices operate in Base Rate Mode (BRM) when MCLK/LRCK is 256, 384 or 512 and in High Rate Mode (HRM) when MCLK/LRCK is 128 or 192. High Rate Mode allows input sample rates up to 100 kHz.



CS4334/5/6/7/8/9 FAQs

FAQs

- 1) What competitive advantages do these D/A converters offer?
A: These DACs provide the smallest and most cost-effective solution for CD quality digital audio.

- 2) What is the difference between High Rate Mode (HRM) and Base Rate Mode (BRM)?
A: These DACs support two oversampling modes. 128× oversampling, BRM, is used for sample rates less than 50 kHz and 64× oversampling, HRM, is used for sample rates greater than 50 kHz. Therefore a 12.288 MHz MCLK can support both 48 kHz and 96 kHz sample rates.

- 3) Are the CS4334, CS4338, and CS4339 drop-in replacements for the CS4331, CS4333, and CS4330 respectively?
A: The CS4334, CS4338, and CS4339 are functionally compatible and have the same pin-out as the CS4331, CS4333, and CS4330 respectively, but are in a smaller package. The new DACs are in an 8-pin 150 mil wide Jedec SOIC package. The CS4330/1/3 are in an 8-pin, 208 mil wide EIAJ SOIC package.



CS4334/5/6/7/8/9 Ordering Information

Ordering Information

Model	Temperature	Package	Serial Interface
CS4334-KS	-10 to +70°C	8-pin Plastic SOIC	16 to 24-bit, I2S
CS4335-KS	-10 to +70°C	8-pin Plastic SOIC	16 to 24-bit, left justified
CS4336-KS	-10 to +70°C	8-pin Plastic SOIC	24-bit, right justified
CS4337-KS	-10 to +70°C	8-pin Plastic SOIC	20-bit, right justified
CS4338-KS	-10 to +70°C	8-pin Plastic SOIC	16-bit, right justified
CS4339-KS	-10 to +70°C	8-pin Plastic SOIC	18-bit, right justified, 32 F _s Internal SCLK mode

Functional Compatibility

CS4330-KS ⇒ CS4339-KS

CS4331-KS ⇒ CS4334-KS


CS4333-KS ⇒ CS4338-KS

For further information on Crystal products, please visit our website “www.crystal.com” or call our literature department (800) 888-5016 ext. 3594 or (512) 912-3594 for data sheets and application notes.

Schematic & Layout Review Service

**Confirm Optimum
Schematic & Layout
Before Building Your Board.**

**For Our Free Review Service
Call Applications Engineering.**



C a l l : (5 1 2) 4 4 5 - 7 2 2 2

Sales Office and Applications Support

UNITED STATES

Western Area

Cirrus Logic, Inc.
3100 West Warren Ave.
Fremont, CA 94538
Ph: 510-623-8300
FAX: 510-252-6020

Southern California, Sales
Westlake Village
The Townsgate Executive Bldg.
2659 Townsgate Road,
Suite 238
Westlake Village, CA 91361
Ph: 805-371-5860
FAX 805-371-5861

Cirrus Logic, Inc.
6650 S.W. Redwood Lane,
Ste. 105, First Floor Bldg. 16
Portland, Oregon 97224
Ph: 503-620-5547
FAX: 503-620-5665

Central Area

Cirrus Logic, Inc.
14205 Burnet Rd., Ste. 400
Austin, TX 78728
Ph: 512-255-8893
FAX: 512-255-0733

Sotheastern Area

Cirrus Logic, Inc..
5511 Capital Center Dr., Ste. 103
Raleigh, NC 27606
Ph: 919-859-5210
FAX: 919-859-5334

Northeastern Area

Cirrus Logic, Inc.
10 New England Business
Center, Ste. 100
Andover, MA 01810
Ph: 978-794-9992
FAX: 978-794-9998

Cirrus Logic, Inc.
10440 Little Patuxent Pkwy.,
Ste. 300
Columbia, MD 21044-3559
Ph: 410-740-5654
FAX: 410-740-6961

EUROPE

Cirrus Logic International SARL
Immeuble Andre Malraux
1 rue de Rome
F-93561 Rosny-sous-Bois
CEDEX, France
Ph: +33148122812
FAX: +33148122810

Cirrus Logic UK.
Anglers Court
4-5 Spittal St.
Marlow
Bucks, England SL7 1DB
Ph: +44(0)1628 472 211
FAX: +44(0)1628 486 114

Cirrus Logic GmbH
Muehlfelder-Strasse 2
D-82211 Herrsching, Germany
Ph: +49815292460
FAX: +498152924699

FAR EAST

China

Cirrus Logic International Ltd.
A-1403, Qiancun Commercial
Mansion
Beijing, China 100029
Ph: (8610)6443-0783
Ph: (8610)6443-0784
Ph: (8610)6443-0785
FAX: (8610)6443-0786

Hong Kong

Cirrus Logic International Ltd.
1203 Park Tower
15 Austin Rd., Tsimshatsui
Kowloon, Hong Kong
Ph: (852)2376-0801
FAX: (852)2375-1202

Korea

Cirrus Logic, Korea Co., Ltd.
Rm 1302 SangKyung
Bldg., 824-21 YeokSam-Dong,
Kang Nam-Ku,
Seoul, Korea
Ph: +82(2)565-8561
FAX: +82(2)565-8565

Singapore

Cirrus Logic International Ltd.
6 Kaki Bukit Ave. 1,
Ste. 03-03
Singapore 417940
Ph: +65-743-4111
FAX: +65-742-4111

Taiwan

Cirrus Logic International Ltd.
Taiwan Branch
10F, No.214 Tun Hwa North Rd.
Taipei, Taiwan R.O.C.
Ph: +886(22)718-4533
FAX: +886(22)718-4526

JAPAN

Cirrus Logic K.K.
Shinjuku Green Tower,
Bldg. 26F
6-14-1 Nishi-Shinjuku,
Shinjuku-ku,
Tokyo, 160
Japan
Ph: +81(03)3340-9111
FAX: +81(03)3340-9120

CRYSTAL
A DIVISION OF  CIRRUS LOGIC®

**CRYSTAL SEMICONDUCTOR
PRODUCTS DIVISION**

**PO BOX 17847
4210 S. INDUSTRIAL DRIVE
AUSTIN, TEXAS 78744
512.445.7222 / 800.888.5016
FAX: 512.445.7581**

**WORLDWIDE WEB:
<http://www.crystal.com>**